QSC SERIES ONE

100DEL 1080

Series One is a direct outgrowth of our research into Series Three, the world's most sophisticated professional amplifiers. Series One is designed for those discriminating users who demand superior audio performance but don't require front-removable channel modules, detented gain controls, or true dual-monaural configuration. Series One benefits from refinements in our time proven circuitry, the use of premium components, and our latest

design techniques.

The Model 1080 is a moderate power, single rack space amplifier designed for professional and commercial audio applications requiring both high performance and high reliability. The result of careful research, the 1080 is loaded with useful features and benefits.

FEATURES:

High-performance, full-complementary circuit.

- Independent DC and sub-audio speaker protection on each
- Delayed turn-on, instant turn-off with pop filter.

Dual power supplies.

Recessed calibrated gain controls.

Active balanced inputs.

- Octal input sockets for active or passive input modules such as crossovers, limiters, or transformers.
- Octal socket programming switches.

- Mono-bridging switch.
 Two ½ "RTS front-mounted stereo headphone jacks.
- 1/4" RTS, XLR, and barrier input connectors.

 5-way binding post output connectors arranged for mono-bridging.

■ Patented Output Averaging™short-circuit protection.

Clipping indicators.

- Large passive heatsinks for ample cooling.
- Direct mounted power transistors.
- Sculptured aluminum front panel.

Two-year warranty.

Premium components throughout:

High-speed, low-noise, low-distortion 5532 op-amp

Large SOA (Safe Operating Area) high-speed, triple-diffused MESA output devices.

High-density, low ESR filter capacitors.







SPECIFICATIONS

OUTPUT POWER (Per Channel)

Continuous Average Output Power both channels driven: 8 ohms, 20-20kHz, 0.1% THD – 35 Watts

4 ohms, 20-20kHz, 0.1% THD - 50 Watts

2 ohms, 20-20kHz, 0.1% THD - 60 Watts

Continuous Average Output Power one channel driven:

8 ohms, 1kHz, 1% THD - 42 Watts 4 ohms, 1kHz, 1% THD - 65 Watts 2 ohms, 1kHz, 1% THD - 80 Watts

4 ohms, 20-20kHz, 0.1% THD - 120 Watts

Continuous Average Output Power bridged-mono operation: 8 ohrns, 20-20kHz, 0.1% THD - 100 Watts

DISTORTION (8 ohms)

THD – 20-20kHz at rated power shall be less than 0.1% SMPTE-IMD less than 0.01% at rated power FREQUENCY RESPONSE 20-20kHz, +0, –0.5dB

DAMPING FACTOR 200 at 8 ohms

DYNAMIC HEADROOM 2dB at 8 ohms

NOISE - 100dB below full output, Aweighted

SENSITIVITY .83V RMS for rated power at 8 ohms

INPUT IMPEDANCE 20k balanced or 10k unbalanced

POWER REQUIREMENTS 110-125V, 60Hz, 2.5A

DIMENSIONS 1.75" Tall X 19" Wide X 8.7" Deep WEIGHT 12 lbs

Specifications subject to change without notice.

ARCHITECTS AND ENGINEERS SPECIFICATIONS

The power amplifier shall contain all solid-slate circuitry, using complementary silicon semiconductors. It shall be capable of operating from 170-125V, 60Hz AC current. The amplifier shall contain two independent channels. Each channel shall have independent protective circuitry against open-circuit, short-circuit, or reactive loads, and the remaining channel shall continue to operate if one channel fails. A multing circuit shall provide three seconds of multing offer turn-on, and shall multe within ½ second after turn-off or loss of power, to protect the load against turn-on or turn-off thumps. Self-resetting thermal shutdown shall protect the circuit graphs the protect against temperatures in excess of 90 degrees C, and a front panel resettable circuit protect against temperatures in excess of 90 degrees C.

breaker shall protect against AC overloads.

Each channel of the amplifier shall be capable of meeting the following performance criterio, with both channels driven simultaneously, unless otherwise stated:

Output power, 8 ohms per channel, 20-20kHz, less than 0.1% distortion, at least 35 watts RMS

per channel

Output power, 4 ohms per channel, 20-20kHz, less than 0.1% distortion, at least 50 watts RMS per channel

Output power, 2 ohms per channel, 20-20kHz, less than 0.1% distortion, at least 60 watts RMS per channel.

Frequency response shall be 20-20 kHz with less than 0.5dB deviation. SMPTE IM distortion shall be less than 0.01% at roled power, 8 ohms, and less than 0.02% at rated power, 4 ohms.

IHF domping factor shall be at least 200.

Signal to noise, below rated output, shall be at least 100dB (Aweighted).

Dynamic Headroom at 8 ohms shall be at least 2dB.

The vollage gain shall be 26dB of full Gain.

The power gain shall be 54dB of full Gain.
The input sensitivity for rated 8-ohm power shall be .83V RMS.
Balanced input impedance shall be 20K ohms; unbalanced input impedance shall be 10K ohms.

Balanced, bridging input circuitry shall be standard, and the amplifier shall meet all performance criteria in the balanced or unbalanced mode.

The amplifier shall have external, passively coaled heatsinks. Each channel shall include the following controls, indicators, and connectors:

Front Mounted gain control, calibrated in dB.

Clipping indicator, responding proportionally to any distortion in excess of 0.1%.

Balanced/Unbalanced input jack of the ¼ "ring-lip-sleeve type (RTS).

Balanced input jack of the ¼R type.

Balanced input of the barrier strip screw terminal type. Octal accessory socket with DC power for active and possive input accessories.

Speaker terminals of the 5-way binding post type.

In addition, the chassis shall feature two stereo headphone jacks, a mano-bridging swilch accessible from the bottom of the amplifier, 8-position microswilches for bypassing the actal sockets, paralleting the two channels, and assigning a single actal accessory to both channels, front mounted AC switch and circuit breaker, and built-in rack mounting ears.

The chassis shall mount in a 19 inch rack, occupying 1 rack space (1.75 inches). Chassis depth behind the rails shall be 8.7 inches. The front profrusion shall be 0.5 inch. Weight shall be

12 lbs.

The amplifier shall be the QSC Model 1080.



QSC AUDIO PRODUCTS INC 1926 PLACENTIA AVENUE COSTA MESA, CA 92627 714-645-2540